

AL LED Indicator

**Short body Indicator.
Stable, Uniform Illumination.**

The pursuit of reflection efficiency realizes unprecedented brightness.

■ FEARTURES

Size : 30×70mm rectangular type.

Depth behind panel: 29.5mm

Terminal : Connector type

Mounting : Snap-in type

Illumination: Mono-Color, Split-Face, Dual-Color,
Negative




SPECIFICATIONS

Insulation Resistance	More than 100MΩ at 500V DC
Dielectric Strength	1500V AC RMS between terminals and ground (50/60Hz for 1 minute)
Reverse Dielectric Strength	400V
Ambient Temperature	-10°C~40°C
Ambient Humidity	45~85%RH


LED DATA

DC Supply Voltage		Current Rating (mA)		
		Red	Green	Yellow
DC24V(±5%)	Mono-Color	12	18	18
	Split-Color	6	9	9
	Dual-Color	12	18	18


STRUCTURE



DIMENSIONS




INTERNAL CONNECTION ARRANGEMENTS




TERMINAL

●TERMINAL LAYOUT



Pin No.	Rectangular (30×70)		
	Full-Face	Dual-Color	Split-Face
1	Anode (+)	Anode (+)	Anode (+)
2	Cathode (-)	Cathode (-)	Cathode (-)
3	Anode (+)	Anode (+)	Anode (+)
4	Cathode (-)	Cathode (-)	Cathode (-)
5			

●CONNECTOR (BL-0077)




●Suitable wire

Wire size	Diameter
AWG#24-28	1.0-1.5mm

●Wire Harness

Wire : UL1061 AWG26



A length	Part No.
50cm	CL-0230
100cm	CL-0231

Pin No.	5	4	3	2	1
Color	Red	Green	Yellow	Blue	Gray

Tolerance : ±0.4mm

PANEL LAYOUT / PANEL CUT DIMENSIONS

Panel thickness: 1mm~5mm

		Panel Layout	Panel Cut Dimensions
30 x 70	Vertical		
	Horizontal		


Panel cut dimension should be after panel paintings.

n: number of indicators

ACCESSORIES


CONNECTOR

Part No. BL-0077




Wire Harness

A length	Part No.
50cm	CL-0230
100cm	CL-0231




FILTER DIMENSIONS

● Full-Face



● Spli-Face



REPLACEMENT PARTS

● FILTER

Item \ Color	Red	Green	Yellow	Clear	Negative Red	Negative Green	Negative Yellow	Negative Clear
Full-Face	AL-0025-R	AL-0025-G	AL-0025-Y	AL-0025-C	AL-0036-R	AL-0036-G	AL-0036-Y	AL-0036-C
Split-Face	AL-0031-R	AL-0031-G	AL-0031-Y	AL-0031-C	AL-0037-R	AL-0037-G	AL-0037-Y	AL-0037-C

● COVER

Clear	Semitransparent (for Negative)
AL-0023-C	AL-0023-SK

● Diffuser Plate


Full-Face	Split-Face
AL-0026	AL-0035

● Divider

Split-Face
AL-1264


DISASSEMBLY

1. Removing Cover



Insert a flat head screwdriver in the recess in the center and turn it by 90°. Please be careful not to damage the cover.

2. Removing Diffuser Plate and Filter



Put it out straight with the removing tool (SJ-0002-1).

Tolerance : ±0.4mm

ORDERING CODE

AL — 1 2 1 2

● ILLUMINATION TYPE

W0	Full-Face
W2	Split-Face
W3	Dual-Color

● LED COLOR

70	Red	Full-Face : Put color no. into the frame 1 Split-Face : Put color no. into the frame 1, 2 Dual-Color : Put color no. into the frame 1, 2 (Combination 7080, 8090, 9070)
80	Green	
90	Yellow	
X	Without LED	

● COVER

C	Clear
SK	Semitransparent for Negative
X	Without Cover

● HOUSING

K	Black
H	Gray

● MOUNTING

1	For Horizontal Mtg.
2	For Vertical Mtg.
X	Without Snap spring

● Supply Voltage to LED

3	24V
X	Without LED

● TERMINAL


K	Connector
---	-----------

● FILTER COLOR

1	Red	Full-Face : Put color no. into the frame 1 Split-Face : Put color no. into the frame 1, 2 Dual-Color : Put 9 into the frame 1
2	Green	
3	Yellow	
9	Clear	
X	Without Filter	

● NOTES

- 1) In case of Split-Face, LED and Filter color location should be specified as follow:



- 2) Simultaneous lighting is possible for Split-Face and Dual-Color.
- 3) Please use exclusive connector (BL-0077). When purchasing a wire harness, connector is unnecessary, please specify 0015 at the end of the model.
- 4) In case of specify a cover for Negative, the filter is black silk printed on one side.
- 5) Snap-spring metal plates come out Left/Right direction for Vertical mounting, and Top/Bottom direction for Horizontal mounting to avoid interfering mutually in case of serial mounting. Therefore, in case of independent use, it does not matter. (select 1 Horizontal ordinary)